

DIY Wooden Planter

By **Erin Spain**

Difficulty

Easy

This indoor DIY wooden planter is a great addition to any room, and can be customized to any color or finish you choose!



Tools

Kreg Tools

Kreg®
Pocket-
Hole Jig
520PRO

[Kreg® Pocket-Hole Jig 520PRO](#)

Other Tools

Saw

Drill

Materials

Wood Products

- 1 1x12 Board , 1x12x6
- 1 1x2 Board , 1x2x6
- 1 2x2 Board , 2x2x6

Hardware & Supplies

- 32 1 1/4" Pocket Hole Screws
- 1 Sanding Block
- 1 Paint Or Stain

Cut List & Parts

- 4 1x12 Boards (For Sides) , 1"x12"x12"
- 4 1x2 Boards (For Bottom Slats) , 1"x2"x13 1/2"
- 4 2x2 Boards (For Legs) , 2"x2"x15"

Directions

1

Cut Your Wood

Cut your wood to the specified dimensions.



2**Drill Pocket Holes**

Drill 3 pocket holes along 2 parallel sides of each 1x12x12 boards, and 1 pocket hole at each end of the 1x2 pieces.

**3****Sand**

Use a sanding block to sand edges smooth.

4**Attach Legs to Front and Back**

Using 1 1/4" pocket hole screws, attach 2 legs to one of the 1x12x12 pieces. Repeat. These will be the front and back of the planter.



5**Attach Sides**

Attach remaining 1x12x12 pieces (the sides) to the front and back you assembled in the previous step.



6**Add Bottom Slats**

Use 1 1/4" pocket hole screws to attach bottom slats (1x2 pieces). You can use a scrap piece of wood as a spacer or just eyeball it and try to space them as evenly as possible. It will not be visible so doesn't have to be perfect.



7**Paint or Stain**

Finish your planter with any paint or stain of your choice.

