


DIY Serving Tray

By **Anika's DIY Life**

Difficulty

Easy

Learn how to build a gorgeous serving tray using basic tools. This is a perfect project for beginners and makes a great handmade gift too.



Tools

Kreg Tools



[Kreg® Pocket-Hole Jig 720](#)



[Cabinet Hardware Jig](#)

Other Tools

Miter Saw

Drill (cordless)

Nail Gun

Shop Vacuum

Tape Measure

Materials

Wood Products

1 Board , 1x8 , 96"

1 Board , 1x3 , 96"

3 Board , 1/4" X 2.5" , 72"

Hardware & Supplies

2 Pulls Of Your Choice

10 1-1/4" Pocket Hole Screws

50 1-1/4" Finish Nails

Cut List & Parts

4 Base Pieces , 3/4" X 8" X 10"

20 Planks , Various

2 Long Sides , 3/4" X 2.5" X 20"

2 Short Sides , 3/4" X 2.5" X 16"

Directions


1

Make cuts for the top pattern

Set the miter saw at 45 degrees and cut out planks from the 1/4" material to lay on the base pieces.

Cut them longer than needed.


Once the pattern is decided, stain them individually.



2**Attach top boards**


Apply wood glue to the base pieces and glue the planks and leave overnight.

Once dry, cut off excess from all sides of the base pieces.



3**Attach base pieces**


Attach base pieces together using 3/4" pocket holes and 1-1/4" pocket hole screws to form the tray base.



4**Add sides**

Attach 1x3 sideboards around the tray using wood glue and 1-1/4" finish nails.

Note - be sure to stain the sides separately before attaching.

**5****Finishing steps**

Apply sealer and add hardware of your choice.

I find it really to use the Kreg hardware jig to ensure everything is perfectly centered.

6**See more**

Read more details on finish and get more tips and tricks - <https://www.anikasdiylife.com/diy-wood-tray/>

Full video of the project - <https://youtu.be/ljNQVTcQnx0>